## **RG58A/U Coax Delay Box**

DB64 — RG58A/U Coax Delay Box



- Switch controlled time delays
- 0 to 63.5 ns delay range
- 0.5 ns resolution
- Low reflections and feed-through

## DB64 Coax Delay Box

The SRS Model DB64 Coax Delay Box provides switchcontrolled delays from 0 to 63.5ns with 0.5ns resolution. Applications include the timing of photomultiplier coincidences, set-up of time-to-amplitude converters, adjustment of signal phase, or any application which requires an adjustable, high-bandwidth analog delay.

The interchangeable inputs/outputs are on BNC connectors. Internally, the delay line segments consist of accurate lengths of RG58A/U coax cable with 50  $\Omega$  characteristic impedance. DPDT switches are used to insert or remove delay segments. Careful component selection, mechanical design, and PCB layout ensure low reflections and low switch feed-through for high speed signals.

Two DB64s can be mounted side-by-side in a 19" rack using the RM1U rack mount accessory. A chassis lug is provided on the rear panel as a safety ground.

Distribution in the UK & Ireland



Characterisation, Measurement & Analysis Lambda Photometrics Limited Lambda House Batford Mill Harpenden Herts AL5 5BZ United Kingdom E: info@lambdaphoto.co.uk W: www.lambdaphoto.co.uk

- T: +44 (0)1582 764334
- F: +44 (0)1582 712084

## **DB64 Specifications**

Connectors	BNC
Characteristic impedance	50 Ω
Delay line cable	RG58A/U (Belden 8259)
Insertion delay	2.5 ns
Delay range	0 to 63.5 ns
Delay resolution	0.5 ns
Delay error	<100 ps + 0.5 % of delay
Signal reflection	<3 %
Switch feed through	<0.8 pF
Maximum voltage	250 Vrms
Maximum current	2 A
Dimensions	8.3" × 1.5" × 8.0" (WHL)
Weight	2 lbs



## **Ordering Information**

DB64 Coax Delay Box RM1U 1U dual rack mount Distribution in the UK & Ireland



Characterisation, Measurement & Analysis

Lambda Photometrics Limited Lambda House Batford Mill Harpenden Herts AL5 5BZ United Kingdom

- E: info@lambdaphoto.co.uk W: www.lambdaphoto.co.uk
- T: +44 (0)1582 764334
- F: +44 (0)1582 712084