

Small Instrumentation Modules

SIM954 — 300 MHz, dual-channel inverting amplifier

- **300 MHz bandwidth**
- **±10 V output voltage**
- **Up to 1 A output current**
- **<1 dB flatness**
- **4000 V/μs slew rate**
- **2 independent channels**



SIM954 300 MHz Amplifier

The SIM954 Amplifier is a 300 MHz, dual-channel inverting amplifier that delivers up to ± 10 V of output voltage and up to 1 A of output current. The amplifier can be used to drive many types of light laboratory loads without imposing the limitations and high cost of typical RF power amplifiers.


Specifications

Bandwidth (−3 dB)	DC to 300 MHz
Gain	12 dB into 50 Ω (inverting)
Gain flatness	<1 dB (DC to 100 MHz)
Crosstalk	−60 dB (at 1 MHz), −40 dB (full BW)
VSWR	1.2:1 (DC to 100 MHz) 1.6:1 (DC to 300 MHz)
Isolation (output to input)	−70 dB (DC to 1 MHz), −40 dB (full BW)
Slew rate	4000 V/μs
Output amplitude	±10 V (into 50 Ω)
Peak output current	1 A (into $\leq 7 \Omega$)
Ave. output current	500 mA (sum of both channels)

Output impedance	3.3 Ω
Input impedance	50 Ω
Input offset voltage	1 mV (trimmable)
Input bias current	1 μA (trimmable)
Operating temperature	0 to 40 °C, non-condensing
Interface	Serial via SIM interface
Connectors	BNC (4 front-panel) DB15 (male) SIM interface
Power	Supplied by SIM900 Mainframe, or optionally by a user-supplied DC power supply (±15 V and +5 V)
Dimensions	1.5" × 3.6" × 7.0" (WHD)
Weight	1.5 lbs.
Warranty	One year parts and labor on defects in materials and workmanship

Ordering Information

SIM954 300 MHz dual-channel amplifier

 Distribution in the UK

Lambda
photometrics

Lambda Photometrics Ltd, Lambda House, Batford Mill, Harpenden, Hertfordshire AL5 5BZ

E: info@lambdaphoto.co.uk W: www.lambdaphoto.co.uk T: +44 (0)1582 764334 F: +44 (0)1582 712084

The leading supplier of scientific and industrial lasers, optical systems and associated accessories, fibre optic components and instrumentation, and machine vision products.